

# Universal Switch List for Z-AUDIO system by HDL Buspro

1/2020

HDL Automation s.r.o.

A command is executing when the UV switch of relevant number (in the table *UV switch No*) is sent to the address of MZ box module.

UV Switch list for Z-AUDIO:

No.	UV Switch No.	Function
1	1-149	ON: Select a song in playlist(song No.1-149) OFF:select a song to stop
2	150-200	ON: Select a playlist(playlist No.0-50) OFF: Do nothing
3	201	ON: Play OFF: Stop
4	202	ON: Stop All OFF: Do nothing
5	203	Change a playlist ON: Next      OFF: <u>Pre</u>
6	204	Change a song ON: Next      OFF: <u>Pre</u>
7	205	Control Audio voice ON: UP      OFF: DOWN
8	206	TREBLE ON: UP      OFF: DOWN
9	207	BASS ON: UP      OFF: DOWN
10	208	ON: Play music on SD-Card
11	209	ON: Play music on FTP server
12	210	ON: Radio
13	211	ON: Audio-in
14	215	Voice 63(Min)
15	216	Voice 55
16	217	Voice 47
17	218	Voice 39
18	219	Voice 28
19	220	Voice 20
20	221	Voice 15
21	222	Voice 10
22	223	Voice 5
23	224	Voice 0(Max)
24	225	Play One
25	226	Repeat One
26	227	Order Play
27	228	Repeat All